









OSRAM SubstiTUBE® T5HO80 37W UNIVERSAL













1.5m Ballast compatibility (1449mm)




 compatible










 not compatible





ST5 HO80 37W UNIVERSAL	
Product EAN10 No.	
4058075137844	
4058075137868	
4058075137882	


	Model	Ref.no	L *	
OSRAM	Qti 1x35/49/80/GII	AA3529702OL	1	
	QTP5 1x80	A63948601DG	1	
	Qti DALI 1X35/49/80 DIM	AA3853501DG	1	
	QTi 2x35/49/80 GII	A74908402DG	2	
	QT-FQ 2x80	A57569D01DG	2	
	Qti DALI 2X35/49/80 DIM	A749084EE209	2	

PHILIPS	HF-P 180 TL5/PL-L III IDC	9137130342	1	
	HF-S 1 80 TL5/PL-L II	9137130422	1	
	HF-Pi 1 28/35/49/80 TL5 EII 220-240	9137006525	1	
	HF-P Xt 180 TL5 EII 220-240V 50/60Hz		1	
	HF-R 180 TL5/PLL EII		1	
	HF-R TD 180 TL5/PL-L EII	9137006066	1	
	HF-P 2 80 TL5/PL-L III IDC	9137130343	2	
	HF-Pi 2 28/35/49/80 TL5 EII 220-240	9137006526	2	
	HF-P Xt 280 TL5 EII 220-240	9137006302	2	
	HF-S 2 80 TL5/PL-L II	9137130423	2	
	HF-Ri TD 280 TL5/PL-L E+	9137006096	2	
	HF-R 280 TL5/PLL EII 220-240	9137006091	2	

VS	ELXc 180.634	188947	1	
	ELXC 180.866	188144	1	
	ELXc 280.538	188619	2	

TRIDONIC	PC 1x80 T5 PRO Ip	22185209	1	
	PC 1/14-35/49/80 T5 PRO-M Ip	22176184	1	
	PC 1/80 T5 INDUSTRY	89800460	1	
	PCA 1x80 T5 BASIC Ip	22185048	1	
	PC 2x80 T5 PRO Ip	22185210	2	
	PC 2/80 T5 INDUSTRY	89800461	2	
	PCA 2X80 T5 EXCEL one4all Ip	22185107	2	
	PCA 2x80 T5 ECO Ip	22185098	2	
	PCA 2x80 T5 BASIC Ip	22185085	2	

BAG	MLS80.1FR-11/220-240	10071608	1	
	MLS80.1/54.2FR-11/220-240 1 x T5 80	10071609	1	
	BCS80.1FX-11/220-240	10077587	1	
	BCS80.2FX-11/220-240	10095407	2	

	Mains 230V			
--	------------	--	--	--

L*: Lamps on ballast

VS= VOSSLOH SCHWABE